



**GOODMAN BENTLEY SPEC/OPS DESIGN & SECURITY
COMPANY**

WATCH SPY CAMERA



This Watch Spy Camera and Receiver is the ultimate covert operations kit. The camera in the watch is so small it's practically undetectable and looks absolutely normal. Smart mounting of the camera results in the image being correctly orientated when the watch is upside down, for example when naturally resting your arm on a table.

With stylish brushed aluminum and black a face no one will ever suspect they are being filmed.

The receiver unit comes with a 2.5 inch LCD and the capability of monitoring 4 wireless cameras at the same time, playing music and even MPEG 4 movies if the mood takes you.

This is quite simply the most covert spy camera we have ever produced.



TECHNICAL SPECIFICATIONS:

MP4 Receiver

- Channels Available: 4
- Receiving Frequency: 2414MHz, 2432MHz, 2450MHz, 2468MHz
- Demodulation Mode: FM
- Antenna: 50ohm SMA
- Channel Scan and Channel Skip for multiple Cameras
- AV OUT/IN (NTSC/ PAL)
- SNR (Signal to Noise Ratio): 90dB
- Memory: 64 MB
- External Memory: SD Card (Up to 4 GB) for Recording and Playback, USB Flash for playback only(Up to 4GB)
- Display: 882x228 2.5 Inch LCD
- Video:
 - Play Formats: MPEG 1, MPEG 4, AVI, ASF, ADPCM

-FPS (Frames per Second): 30fps
-Capture Format: MPEG 4 AVI
-Capture Resolution: 640x480 / 320x240
-Capture Compression Settings: Standard, Better, Best

- **Audio:**
 - Music Format: MPEG3
 - Output of Earphone Jack: 20mW+20mW
 - Output of Speaker: 1W
 - Frequency Range: 20Hz to 20kHz
- **Picture Format: JPEG**
- **Languages: English, Chinese**
- **USB: 2.0**
- **System: Windows 98SE/ME/2000/XP/Vista**
- **Power Source: 5 VDC**
- **Internal Battery: Li Ion 2500mAh**
- **Dimensions: 119 x 260 x 69mm (L x W x D)**

Camera Specifications

- **Image Device: 1/4 Inch CMOS Colour Sensor**
- **TV system: AUTO- NTSC: 510x490, PAL:380x296**
- **Horizontal Definition: AUTO- NTSC: 380 TV lines, PAL 240 TV Lines**
- **Angular Field of View: 60 degrees**
- **Minimum Illumination: 2.0 lux**
- **Synchronization System: Internal**
- **Backlight Compensation: Auto**
- **White Balance: Auto**
- **S/N Ratio of built in Microphone: 55dB**
- **Operation Temperature:**
- **Transmission Frequencies :2414MHz, 2432MHz, 2450MHz, 2468MHz**
- **Power Source: 5 VDC**
- **Internal Battery: 130 mAh (up to 40 minutes operating time)**
- **Transmission Range: Up to 200feet Line of Sight (LOS)**
- **Dimension: Watch Face 45mm diameter x 16mm deep**

Other Features:

- **Built in Mircrophone**
- **Multiple Charging Options**
- **Working Watch with Quality Movement**
- **Ultra Covert, Practically Undetectable**

Accessories:

- **User Manuals**
- **Earphones**
- **USB Cords**
- **Solar Power Brick / Charger with Cabling**
- **Mains Power Adaptor**
- **AV (stereo) out cord (3xRCA to 3.5mm plug)**

email: enquiries@goodmanbentley.com
