



GOODMAN-BENTLEY
(SPEC/OPS) DESIGN & SECURITY
COMPANY

WOLFEYES 6A SNIPER RECHARGEABLE Tactical Torch Technical Specifications & Instructions

Contains:

- 1 x SNIPER Body with 6A tactical button tail-cap as an option
- 1 x 3.7v Lamp Assembly
- 1 x LRB-168A Li-ion Rechargeable Battery
- 1 x CH-02 fast smart AC Charger, 3 hours charging (MAX)
- 1 x Gift Box

Installing & Using:

- A. Screw off the Head Cap
- B. Insert the lamp Assembly into the head cap (only on replacement) already inserted
- C. Insert the battery into the housing, anode towards the body tail end
- D. Screw the head cap on
- E. Depress the tail-cap button lightly for Morse on, and Depress the button fully down for lock on.
- F. Screw the head cap off slightly to disable the light from activating when being carried, packing or storage for safety

IMPORTANT

DO NOT USE ANY OTHER KIND OF BATTERY SUCH AS THE CR123 BATTERIES WITH THIS TORCH. OTHERWISE THE 3.7V LAMP WILL BURN OUT. ONLY USE THE RECHARGEABLE BATTERY SUPPLIED.
NEVER SHINE THE LAMP INTO HUMAN EYES AT SHORT DISTANCE AS THIS WILL CAUSE DAMAGE

Specification:

1. Brightness and runtime: 120 Lumens (max) / 60 minutes constant on after every full charge using the rechargeable batteries supplied.
2. Body: Aircraft Aluminium Construction
3. Reflector: High Temperature processed layers of alloy coated film
4. Finish: Low Temperature (-20C) hard- anodised (HA) finish treatment
5. Lamp: 3.7volt xenon high colour temperature, daylight effect focussing
6. Switch: Rapid switch between Morse-on and Lock-on with over 50,000 times life cycle
7. 'O' ring sealed: Splash Proof
8. Beam: Special Design of Flawless beam, perfect light sources for photography
9. Colour Temperature: Above 3600K
10. Weight without battery: 138g
11. Length: 130mm
12. Body Diameter: 25.4mm
13. Head Diameter : 35mm
14. Operation Temperature: -25C – 60C